



FAN6747WALMY

Highly Integrated Green-Mode PWM Controller

Features

- High-Voltage Startup
- AC-Line Brownout Protection by HV Pin
- Constant Output Power Limit by HV Pin (Full AC-Line Range)
- Built-in 8ms Soft-Start Function
- Leading-Edge Blanking (LEB)
- Short-Circuit Protection (SCP) with 15ms Debounce Time as Output Short
- Peak-Current Mode Operation with Cycle-by-Cycle Current Limiting
- Low Startup Current: 30µA
- Low Operating Current: 1.7mA
- Over-Temperature Protection (OTP) with External Negative-Temperature-Coefficient (NTC) Thermistor
- PWM Frequency Decreasing at Green-Mode
- V_{DD} Over-Voltage Protection (OVP)
- Internal Latch Circuit for OVP, OTP, SCP, and OCP

Applications

General-purpose switched-mode power supplies (SMPS) and flyback power converters, including:

- Power Adapters
- SMPS with Peak-Current Output, such as for Printers, Scanners, and Motor Drivers
- AC/DC NB Adapters
- Open-Frame SMPS

Description

The highly integrated FAN6747WA PWM controller provides several features to enhance the performance of flyback converters. To minimize standby power consumption, a proprietary Green-Mode function provides off-time modulation to decrease the switching frequency with load condition.

Under zero-load condition, the power supply enters Burst Mode. Burst frequency can be low to reduce power. Green Mode enables the power supply to meet international power conservation requirements.

The FAN6747WA is specially designed for SMPS with peak-current output. It incorporates a cycle-by-cycle current limiting and Over-Current-Protection (OCP) that can handle peak load with a debounce time. Once the current is over the threshold level, it triggers the first counter for 15ms and checks if V_{DD} is below 11.5V. If it is, the PWM latches off for SCP. If V_{DD} is higher than 11.5V; it keeps counting for 860ms, then the PWM latches off for OCP.

FAN6747WA also integrates a frequency-hopping function that helps reduce EMI emission of a power supply with minimum line filters. The built-in synchronized slope compensation helps achieve stable peak-current control. To keep constant output power limit over the universal AC input range, the current limit is adjusted according to AC line voltage detected by the HV pin. The gate output is clamped at 14V to protect the external MOSFET from over-voltage damage.

Other protection functions include AC-line brownout protection with hysteresis and V_{DD} Over-Voltage Protection (OVP). For Over-Temperature Protection (OTP), an external NTC thermistor can be applied to sense the ambient temperature. When OCP, OVP, SCP, or OTP is activated, an internal latch circuit latches off the controller. The latch is reset when the V_{DD} supply is removed.

Ordering Information

Part Number	Operating Temperature Range	Package	Packing Method
FAN6747WALMY	-40 to +105°C	8-Lead, Small-Outline Integrated Circuit (SOIC), JEDEC MS-012, .15-Inch Narrow Body	Tape & Reel

Application Diagram




Figure 1. Typical Application

Internal Block Diagram





Figure 2. Functional Block Diagram

Marking Information



F: Fairchild Logo
Z: Plant Code
X: Year Code
Y: Week Code
TT: Die Run Code
F: L = OCP Latch
T: Package Type (N =DIP, M = SOP)
P: Y = Green Compound
M: Manufacturing Flow Code

Figure 3. Top Mark

Pin Configuration




Figure 4. Pin Assignments

Pin Definitions

Pin #	Name	Description
1	GND	Ground. This pin is used for the ground potential of all the pins. A 0.1 μ F decoupling capacitor placed between VDD and GND is recommended.
2	FB	Feedback. The output voltage feedback information from the external compensation circuit is fed into this pin. The PWM duty cycle is determined from this pin and the current-sense signal from Pin 6 (SENSE).
3	NC	No Connection.
4	HV	High-Voltage Startup. This pin is connected to the line input via diodes and resistors to meet brownout and high/low line compensation. Once the voltage of the HV pin is lower than the brownout voltage, PWM output is turned off. High/low line compensation dominates the Over-Current Protection (OCP) level and cycle-by-cycle current limit to solve the unequal OCP level and power-limit problem under universal input.
5	RT	Over-Temperature Protection. For Over-Temperature Protection (OTP), an external NTC thermistor is connected from this pin to GND. The impedance of the NTC decreases at high temperatures. Once the voltage of the RT pin drops below the threshold voltage, the controller latches off the PWM. If the RT pin is not connected to the NTC resistor for over-temperature protection, it is recommended to place one 100K Ω resistor to ground to prevent noise interference. This pin is limited by an internal clamping circuit.
6	SENSE	Current Sense. This pin is used to sense the MOSFET current for the Current-Mode PWM and OCP. If the switching current is higher than the OCP threshold and lasts for 860ms, the controller latches off the PWM.
7	VDD	Supply Voltage. IC operating current and MOSFET driving current are supplied using this pin. This pin is connected to an external bulk capacitor of typically 10 μ F. The threshold voltages for startup and turn-off are 17V and 10V, respectively. The operating current is lower than 2mA.
8	GATE	Gate Driver Output. The totem-pole output driver for the power MOSFET. It is internally clamped below 14V.

Absolute Maximum Ratings

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only.

Symbol	Parameter	Min.	Max.	Unit
V _{DD}	DC Supply Voltage		30	V
V _{HV}	Suddenly Input Voltage to HV Pin within 1 Second (Series connect with R _{HV})		640	V
V _L	Input Voltage to FB, SENSE, and RT Pins	-0.3	7.0	V
P _D	Power Dissipation (T _A <50°C)		400	mW
θ _{JA}	Thermal Resistance (Junction-to-Ambient)		150	°C/W
T _J	Operating Junction Temperature	-40	+125	°C
T _{STG}	Storage Temperature Range	-55	+150	°C
T _L	Lead Temperature (Soldering, 10 Seconds)		+260	°C
ESD	Electrostatic Discharge Capability, All Pins Except HV Pin	Human Body Model, JESD22-A114	5	kV
		Charge Device Model, JESD22-C101	2	

Notes:

1. Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device.
2. All voltage values, except differential voltages, are given with respect to the network ground terminal.
3. ESD with HV pin: CDM=1250V and HBM=1000V.
4. ESD without HV pin: CDM and HBM sign actual level (no derating).

Recommended Operating Conditions

The Recommended Operating Conditions table defines the conditions for actual device operation. Recommended operating conditions are specified to ensure optimal performance to the datasheet specifications. Fairchild does not recommend exceeding them or designing to Absolute Maximum Ratings.

Symbol	Parameter	Min.	Typ.	Max.	Unit
T _A	Operating Ambient Temperature	-40		+105	°C
V _{HV}	Input Voltage to HV Pin			500	V
R _{HV}	HV Startup Resistor	150	200	250	kΩ

Electrical Characteristics

$V_{DD}=15V$ and $T_A=25^{\circ}C$, unless otherwise specified.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
V_{DD} Section						
V _{OP}	Continuously Operating Voltage				24	V
V _{DD-ON}	Turn-On Threshold Voltage		16	17	18	V
V _{DD-OFF}	PWM Turn-Off Threshold Voltage		9	10	11	V
V _{DD-OLP}	Threshold Voltage on V _{DD} for HV JFET Turn-On in Protection Condition	After Trigger OCP/ SCP/ OVP/ OTP	5.5	6.5	7.5	V
V _{DD-LH}	Threshold Voltage on VDD Pin for Latch-Off Release Voltage		3.5	4.0	4.5	V
V _{DD-AC}	Threshold Voltage on VDD Pin for Disable AC Recovery to Avoid Startup Failed		V _{DD-OFF} +3	V _{DD-OFF} +3.5	V _{DD-OFF} +4	V
V _{DD-SCP}	Threshold Voltage on VDD Pin for Short-Circuit Protection (SCP)	V _{FB} > V _{FB0}	V _{DD-OFF} +1	V _{DD-OFF} +1.5	V _{DD-OFF} +2	V
I _{LH}	Holding Current Under Latch-Off Conduction	V _{DD} =5V	80	100	120	μA
I _{DD-ST}	Startup Current	V _{DD-ON} - 0.16V			30	μA
I _{DD-OLP}	Holding Current at PWM-Off Phase	V _{DD-OLP} +0.1V	180	240	300	μA
I _{DD-OP1}	Operating Supply Current when PWM Operating	V _{DD} =20V, V _{FB} =3V Gate Open		1.7	2.0	mA
I _{DD-OP2}	Operating Supply Current when PWM Stop	V _{DD} =20V, V _{FB} =3V Gate Open		1.2	1.5	mA
V _{DD-OVP}	Threshold Voltage on VDD Pin for V _{DD} Over-Voltage Protection (Latch-Off)		24	25	26	V
t _{D-OVP}	V _{DD} OVP Debounce Time	V _{FB} > V _{FB-N}	75	160	245	μs

Continued on the following page...




Figure 5. UVLO Specification

Electrical Characteristics (Continued)

$V_{DD}=15V$ and $T_A=25^\circ C$, unless otherwise specified.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
HV Section						
I_{HV}	Supply Current Drawn from HV Pin	$V_{HV}=120V, V_{DD}=0V$	1.50	2.75	5.00	mA
V_{IN-OFF}	PWM Turn-Off Threshold	DC Source Series $R=200k\Omega$ to HV Pin	92	102	112	V
V_{IN-ON}	PWM Turn-On Threshold	DC Source Series $R=200k\Omega$ to HV Pin	104	114	124	V
ΔV_{IN}	Change in V_{IN} , $V_{IN-ON} - V_{IN-OFF}$	DC Source Series $R=200k\Omega$ to HV Pin	6	12	18	V
$t_{S-CYCLE}$	Line Voltage Sample Cycle	$V_{FB} > V_{FB-N}$	170	205	240	μs
		$V_{FB} < V_{FB-G}$	450	615	780	
t_{S-TIME}	Line Voltage Sample Period			20		μs
$t_{D_VIN-OFF}$	PWM Turn-Off Debounce Time	$V_{FB} > V_{FB-N}$	65	75	85	ms
		$V_{FB} < V_{FB-G}$	180	235	290	ms

Continued on following page...




Figure 6. Normal UVLO and Two-Step UVLO Behavior




Figure 7. Brownout Circuit

Electrical Characteristics (Continued)




Figure 8. Brownout Behavior




Figure 9. V_{DD-AC} and AC Recovery

Electrical Characteristics (Continued)

$V_{DD}=15V$ and $T_A=25^{\circ}C$, unless otherwise specified.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
Oscillator Section						
f_{OSC}	Normal PWM Frequency	Center Frequency ($V_{FB}>V_{FB-N}$)	61	65	69	kHz
t_{JTR}	Hopping Period			4.8		ms
f_{OSC-G}	Green-Mode Minimum Frequency		20	23	26	kHz
V_{FB-N}	FB Threshold Voltage for Frequency Reduction Beginning	Pin, FB Voltage ($V_{FB}=V_{FB-N}$), $f_{OSC} - 5KHZ$	2.6	2.8	3.0	V
		Hopping Range	± 3.7	± 4.2	± 4.7	kHz
V_{FB-G}	FB Threshold Voltage for Turn-Off Hopping and Frequency Reduction Destination	FB Voltage ($V_{FB}=V_{FB-G}$)	2.1	2.3	2.5	V
		Hopping Range		± 1.45		kHz
V_{OZ-ON}	FB Threshold Voltage for Zero-Duty Recovery		1.6	1.8	2.0	V
V_{FB-ZDC} (V_{OZ-OFF})	FB Threshold Voltage for Zero-Duty		1.5	1.7	1.9	V
V_{OZ-ON} - V_{OZ-OFF}	FB Voltage Hysteresis for V_{OZ-ON} to V_{OZ-OFF}		50	100	150	mV
f_{DV}	Frequency Variation vs. V_{DD} Deviation	$V_{DD}=12V$ to $22V$			5	%
f_{DT}	Frequency Variation vs. Temperature Deviation	$T_A=-40$ to $105^{\circ}C$			5	%

Continued on following page...




Figure 10. PWM Frequency




Figure 11. Burst-Mode Diagram

Electrical Characteristics (Continued)

$V_{DD}=15V$ and $T_A=25^{\circ}C$, unless otherwise specified.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
Feedback Input Section						
A_V	Input-Voltage to Current-Sense Attenuation	$V_{FB} < V_{FB-G}$	1/4.5	1/4.0	1/3.5	V/V
Z_{FB}	Input Impedance		14	16	18	k Ω
V_{FBO}	FB Pin Open Voltage		4.8	5.0	5.2	V
V_{FB-OLP}	FB Open-Loop Protection Threshold Voltage		4.3	4.6	4.9	V
t_{D-OLP}	Open-Loop Protection Debounce time	$V_{FB} > V_{FB-OLP}$	760	860	960	ms
Current Sense Section						
t_{PD}	Delay to Output			65	200	ns
t_{LEB}	Leading-Edge Blanking Time		230	270	310	ns
$V_{limit-L}(V_{ocp-L})$	Current Limit at Low Line ($V_{AC-RMS}=86V$)	$V_{DC}=122V$, Series $R=200k\Omega$ to HV	0.790	0.825	0.860	V
$V_{limit-H}(V_{ocp-H})$	Current Limit at High Line ($V_{AC-RMS}=259V$)	$V_{DC}=366V$, Series $R=200k\Omega$ to HV	0.690	0.725	0.760	V
$t_{SOFT-START}$	Period During Startup	Startup Time	7	8	9	ms
t_{D-OCP}	Debounce Time for Output OCP	$V_{CS} > V_{limit}$	760	860	960	ms
t_{D-SCP}	Debounce Time for Output SCP	$V_{CS} > V_{OCP}$ and $V_{DD} < V_{DD-SCP}$	10.5	13.5	16.5	ms
PWM Output Section						
DCY_{MAX}	Maximum Duty Cycle		82	87	92	%
V_{OL}	Output Voltage Low	$V_{DD}=15V$, $I_O=50mA$			1.5	V
V_{OH}	Output Voltage High	$V_{DD}=12V$, $I_O=50mA$	8			V
t_R	Rising Time	GATE=1nF		95		ns
t_F	Falling Time	GATE=1nF		30		ns
V_{CLAMP}	Gate Output Clamping Voltage	$V_{DD}=22V$	11.0	13.5	16.0	V
Over-Temperature Protection Section						
I_{RT}	Output Current of RT Pin		92	100	108	μA
$V_{OTP-LATCH-OFF}$	Threshold Voltage for Over-Temperature Protection		1.00	1.05	1.10	V
$t_{D_OTP-LATCH}$	Over-Temperature Latch-Off Debounce Time	$V_{FB} > V_{FB-N}$	14	16	18	ms
		$V_{FB} < V_{FB-G}$	40	51	62	ms
$V_{OTP2-LATCH-OFF}$	Second Threshold Voltage for Over-Temperature Protection		0.65	0.70	0.75	V
$t_{D_OTP2-LATCH}$	Second Over-Temperature Latch-Off Debounce Time	$V_{FB} > V_{FB-N}$	110	185	260	μs
		$V_{FB} < V_{FB-G}$	320	605	890	

Typical Performance Characteristics




Figure 12. Startup Current (I_{DD-ST}) vs. Temperature




Figure 13. Operation Supply Current (I_{DD-OP1}) vs. Temperature




Figure 14. Start Threshold Voltage (V_{DD-ON}) vs. Temperature




Figure 15. Minimum Operating Voltage (V_{DD-OFF}) vs. Temperature




Figure 16. Supply Current Drawn from HV Pin (I_{HV}) vs. Temperature




Figure 17. HV Pin Leakage Current After Startup (I_{HV-LC}) vs. Temperature




Figure 18. Frequency in Normal Mode (f_{osc}) vs. Temperature




Figure 19. Maximum Duty Cycle (DCY_{MAX}) vs. Temperature

Typical Performance Characteristics




Figure 20. FB Open-Loop Trigger Level (V_{FB-OLP}) vs. Temperature




Figure 21. Debounce Time of FB Pin Open-Loop Protection (t_{D-OLP}) vs. Temperature




Figure 22. V_{DD} Over-Voltage Protection (V_{DD-OVP}) vs. Temperature




Figure 23. Output Current from RT Pin (I_{RT}) vs. Temperature




Figure 24. Over-Temperature Protection Threshold Voltage (V_{OTP}) vs. Temperature




Figure 25. Over-Temperature Protection Threshold Voltage (V_{OTP2}) vs. Temperature




Figure 26. Brown-In (V_{IN-ON}) vs. Temperature




Figure 27. Brownout (V_{IN-OFF}) vs. Temperature

Operation Description

Startup Current

For startup, the HV pin is connected to the line input through an external diode and resistor, R_{HV} , (1N4007 / 200K Ω recommended). Peak startup current drawn from the HV pin is $(V_{AC} \times \sqrt{2}) / R_{HV}$ and charges the hold-up capacitor through the diode and resistor. When the V_{DD} capacitor level reaches V_{DD-ON} , the startup current switches off. At this moment, the V_{DD} capacitor only supplies the FAN6747WA to maintain the V_{DD} before the auxiliary winding of the main transformer provides the operating current.

Operating Current

Operating current is around 1.7mA. The low operating current enables better efficiency, power consumption, and reduces the required V_{DD} hold-up capacitance.

Green-Mode Operation

The proprietary Green-Mode function provides off-time modulation to reduce the switching frequency in light-load and no-load conditions. V_{FB} , which is derived from the voltage feedback loop, is taken as the reference. Once V_{FB} is lower than the threshold voltage, switching frequency is continuously decreased to the minimum Green-Mode frequency of around 23kHz.

Current Sensing / PWM Current Limiting

The cycle-by-cycle current limiting shuts down the PWM immediately when the sense voltage is over the limited threshold voltage (0.825V at low line). Additionally, when the sense voltage is higher than the OCP threshold (0.825V at low line), the internal counter counts for 860ms latches off PWM. When OCP occurs, PWM output is turned off and V_{DD} begins decreasing.

When V_{DD} goes below the turn-off threshold ($\sim 10V$), the controller is totally shut down. V_{DD} continues to discharge below V_{DD-OLP} by I_{DD-OLP} . Then V_{DD} is charged up to the turn-on threshold voltage of 17V through the startup resistor. When V_{DD} is charged to 17V, it cycles again. This phenomenon is called two-level UVLO.

Brownout and Constant Power Limited HV Pin

The HV pin can detect the peak value of AC line voltage for brownout function and adjust the current-limit level for constant output power limit. Through two fast diodes and startup resistor to sample the AC line voltage, the peak value is refreshed and stored in a register at each sampling cycle.

Equations 1 and 2 calculate the level of brown-in and brownout in RMS value:

$$V_{AC-ON} \text{ (RMS)} = 0.9V \times \frac{(R_{HV} + 1.6)}{1.6} \gamma \sqrt{2} \quad (1)$$

$$V_{AC-OFF} \text{ (RMS)} = 0.81V \times \frac{(R_{HV} + 1.6)}{1.6} \gamma \sqrt{2} \quad (2)$$

where R_{HV} is in k Ω .

The HV pin can perform current limit to shrink the tolerance of Over-Current Protection (OCP) under the full range of AC voltage to linearly current limit curve, as shown in Figure 28.




Figure 28. Linearly Current Limit Curve

Short-Circuit Protection (SCP)

This protection is used to handle the huge output demand if the power supply output is suddenly shorted to ground. If V_{DD} drops under 11.5V and the sensed voltage is higher than the limited threshold voltage, SCP is triggered and PWM output is latched off. This latch condition is reset only if V_{DD} is discharged under 4V.

Under-Voltage Lockout (UVLO)

The turn-on and turn-off thresholds are fixed internally at 17V and 10V, respectively. During startup, the hold-up capacitor must be charged to 17V through the startup resistor to enable the IC. The hold-up capacitor continues to supply V_{DD} before the energy can be delivered from auxiliary winding of the main transformer. V_{DD} must not drop below 10V during startup. This UVLO hysteresis window ensures that the hold-up capacitor is adequate to supply V_{DD} during startup.

Leading-Edge Blanking (LEB)

Each time the power MOSFET is switched on, a turn-on spike occurs on the sense-resistor. To avoid premature termination of the switching pulse, a leading-edge blanking time is built in. During this blanking period, the current-limit comparator is disabled and cannot switch off the gate driver.

Gate Output / Soft Driving

The BiCMOS output stage is a fast totem-pole gate driver. Cross conduction has been avoided to minimize heat dissipation, increase efficiency, and enhance reliability. The output driver is clamped by an internal 13.5V Zener diode to protect power MOSFET transistors against undesirable gate over voltage. A soft-driving waveform is implemented to minimize EMI.

V_{DD} Over-Voltage Protection (OVP)

V_{DD} over-voltage protection prevents damage due to abnormal conditions. If the V_{DD} voltage is over the over-voltage protection voltage (V_{DD-OVP}) and lasts for t_{D-OVP}, the PWM pulses are disabled until the V_{DD} voltage drops below 4V, then restarts. Over-voltage conditions are usually caused by open feedback loops.

Soft-Start

For many applications, it is necessary to minimize the inrush current at startup. The built-in 8ms soft-start circuit significantly reduces the startup current spike and output voltage overshoot.

Built-In Slope Compensation

The sensed voltage across the current-sense resistor is used for peak-current-mode control and pulse-by-pulse current limiting. Built-in slope compensation improves stability and prevents sub-harmonic oscillation. FAN6747WA inserts a synchronized, positive-going ramp at every switching cycle.

Constant Output Power Limit

When the SENSE voltage across sense resistor R_s reaches the threshold voltage, the output GATE drive is turned off after a small delay, t_{PD}. This delay introduces an additional current proportional to t_{PD} • V_{IN} / L_p. Since the delay is nearly constant regardless of the input voltage V_{IN}, higher input voltage results in a larger additional current and the output power limit is higher than under low input line voltage. To compensate this variation for a wide AC input range, a power-limiter is controlled by the HV pin to solve the unequal power-limit problem. The power limiter is fed to the inverting input of the OCP comparator. This results in a lower current limit at high-line input than at low-line input.

Over-Temperature Protection (OTP)

A NTC thermistor, R_{NTC}, in series with a resistor, R_A, is connected from the RT pin to GND pin. A constant current I_{RT} is output from this pin. The voltage of the RT pin can be expressed as V_{RT} = I_{RT} • (R_{NTC} + R_A), where I_{RT} is 100μA. The headroom of V_{RT} is limited at around 5V by internal circuitry. As high ambient temperatures occur, R_{NTC} is smaller, such that the V_{RT} decreases. When V_{RT} is less than 1.05V (V_{OTP}) but over 0.7V, the PWM turns off after t_{D-OTP-LATCH}. The other threshold, V_{DD} under 0.7V, is used for fast shutdown after a short time. If RT pin is not connected to an NTC resistor for Over-Temperature Protection, it is recommended to place one 100KΩ resistor to ground to prevent noise interference. The RT pin is limited by an internal clamping circuit.

Noise Immunity

Noise on the current sense or control signal may cause significant pulse-width jitter, particularly in Continuous-Conduction Mode. Slope compensation helps alleviate this problem. Good placement and layout practices should be followed. Avoiding long PCB traces and component leads, locating compensation and filter components near the FAN6747WA, and increasing the power MOS gate resistance improve performance.

Physical Dimensions




Figure 29. 8-Lead, Small Outline Integrated Circuit (SOIC) Package




Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings:
<http://www.fairchildsemi.com/packaging/>.



TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

- | | | | |
|--|--|--|---|
| 2Cool™ | F-PFS™ | PowerTrench® | The Power Franchise® |
| AccuPower™ | FRFET® | PowerXS™ | the power franchise |
| AX-CAP™* | Global Power Resource™ | Programmable Active Droop™ | TinyBoost™ |
| BitSiC™ | GreenBridge™ | QFET® | TinyBuck™ |
| Build it Now™ | Green FPS™ | QS™ | TinyCalc™ |
| CorePLUS™ | Green FPS™ e-Series™ | Quiet Series™ | TinyLogic® |
| CorePOWER™ | Gmax™ | RapidConfigure™ | TINYOPTO™ |
| CROSSVOLT™ | GTO™ |  ™ | TinyPower™ |
| CTL™ | IntelliMAX™ | Saving our world, 1mW/W/kW at a time™ | TinyPWM™ |
| Current Transfer Logic™ | ISOPLANAR™ | SignalWise™ | TinyWire™ |
| DEUXPEED® | Making Small Speakers Sound Louder and Better™ | SmartMax™ | TransiC™ |
| Dual Cool™ | MegaBuck™ | SMART START™ | TriFault Detect™ |
| EcoSPARK® | MICROCOUPLER™ | Solutions for Your Success™ | TRUECURRENT®* |
| EfficientMax™ | MicroFET™ | SPM® | µSerDes™ |
| ESBC™ | MicroPak™ | STEALTH™ |  SerDes™ |
|  Fairchild® | MicroPak2™ | SuperFET® | UHC® |
| Fairchild Semiconductor® | MillerDrive™ | SuperSOT™-3 | Ultra FRFET™ |
| FACT Quiet Series™ | MotionMax™ | SuperSOT™-6 | UniFET™ |
| FACT® | mWSaver™ | SuperSOT™-8 | VCX™ |
| FAST® | OptoHi™ | SupreMOS® | VisualMax™ |
| FastvCore™ | OPTOLOGIC® | SyncFET™ | VoltagePlus™ |
| FETBench™ | OPTOPLANAR® | Sync-Lock™ | XS™ |
| FlashWriter®* | |  SYSTEM GENERAL®* | |
| FPS™ | | | |

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 162