

LM6125,LM6225,LM6325

LM6125/LM6225/LM6325 High Speed Buffer



Literature Number: SNOSC09

LM6125/LM6225/LM6325 High Speed Buffer

General Description

The LM6125 family of high speed unity gain buffers slew at 800 V/ μ s and have a small signal bandwidth of 50 MHz while driving a 50 Ω load. These buffers drive ± 300 mA peak and do not oscillate while driving large capacitive loads. The LM6125 contains unique features not found in power buffers; these include current limit, thermal shutdown, electronic shutdown, and an error flag that warns of fault conditions.

These buffers are built with National's VIP™ (Vertically Integrated PNP) process which provides fast PNP transistors that are true complements to the already fast NPN devices. This advanced junction-isolated process delivers high speed performance without the need for complex and expensive dielectric isolation.

Features



- High slew rate: 800 V/ μ s

- High output current: ± 300 mA
- Stable with large capacitive loads
- Current and thermal limiting
- Electronic shutdown
- 5V to ± 15 V operation guaranteed
- Fully specified to drive 50 Ω lines

Applications


- Line Driving
- Radar
- Sonar

Simplified Schematic and Block Diagram




Numbers in () are for 14-pin N DIP.

Pin Configurations



*Heat sinking pins.
Internally connected to V-.

**Order Number LM6225N
or LM6325N
See NS Package Number N14A**



Note: Pin 4 connected to case

**Top View
Order Number LM6125H/883 (Note 1)
or LM6125H
See NS Package Number H08C**

Note 1: Available per 5962-9081501

Absolute Maximum Ratings (Note 2)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

Supply Voltage	36V (±18V)
Input to Output Voltage (Note 2)	±7V
Input Voltage	±V _{supply}
Output Short-Circuit to GND (Note 3)	Continuous
Flag Output Voltage	GND ≤ V _{flag} ≤ +V _{supply}
Storage Temperature Range	–65°C to +150°C
Lead Temperature (Soldering, 10 seconds)	260°C

ESD Tolerance (Note 9)	±1500V
θ _{JA} (Note 4)	
H Package	150°C/W
N Package	40°C/W
Maximum Junction Temperature (T _J)	150°C
Operating Temperature Range	
LM6125	–55°C to +125°C
LM6225	–40°C to +85°C
LM6325	0°C to +70°C
Operating Supply Voltage Range	4.75V to ±16V

DC Electrical Characteristics

The following specifications apply for Supply Voltage = ±15V, V_{CM} = 0, R_L ≥ 100 kΩ and R_S = 50Ω unless otherwise noted. **Boldface** limits apply for T_A = T_J = T_{MIN} to T_{MAX}; all other limits T_A = T_J = 25°C.

Symbol	Parameter	Conditions	Typ	LM6125	LM6225	LM6325	Units
				Limit (Notes 5, 10)	Limit (Note 5)	Limit (Note 5)	
A _{V1}	Voltage Gain 1	R _L = 1kΩ, V _{IN} = ±10V	0.990	0.980 0.970	0.980 0.950	0.970 0.950	V/V Min
A _{V2}	Voltage Gain 2	R _L = 50Ω, V _{IN} = ±10V	0.900	0.860 0.800	0.860 0.820	0.850 0.820	
A _{V3}	Voltage Gain 3 (Note 6)	R _L = 50Ω, V ₊ = 5V V _{IN} = 2 V _{PP} (1.5 V_{PP})	0.840	0.780 0.750	0.780 0.700	0.750 0.700	
V _{OS}	Offset Voltage	R _L = 1 kΩ	15	30 50	30 60	50 100	mV Max
I _B	Input Bias Current	R _L = 1 kΩ, R _S = 10 kΩ	1	4 7	4 7	5 7	μA Max
R _{IN}	Input Resistance	R _L = 50Ω	5				MΩ
C _{IN}	Input Capacitance		3.5				pF
R _O	Output Resistance	I _{OUT} = ±10 mA	3	5 10	5 10	5 6	Ω Max
I _{S1}	Supply Current 1	R _L = ∞	15	18 20	18 20	20 22	mA Max
I _{S2}	Supply Current 2	R _L = ∞, V ₊ = 5V	14	16 18	16 18	18 20	
I _{S/D}	Supply Current in Shutdown	R _L = ∞, V _± = ±15V	1.1	1.5 2.0	1.5 2.0	1.5 2.0	
V _{O1}	Output Swing 1	R _L = 1 kΩ	13.5	13.3 13	13.3 13	13.2 13	±V Min
V _{O2}	Output Swing 2	R _L = 100Ω	12.7	11.5 10	11.5 10	11 10	
V _{O3}	Output Swing 3	R _L = 50Ω	12	11 9	11 9	10 9	
V _{O4}	Output Swing 4	R _L = 50Ω	1.8	1.6 1.3	1.6 1.4	1.6 1.5	V _{PP} Min
PSRR	Power Supply Rejection Ratio	V ₊ = 5V (Note 6)	70	60 55	60 50	60 50	dB Min
V _{OL}	Flag Pin Output Low Voltage	V _± = ±5V to ±15V V _{S/D} = 0V		300 400	300 400	340 400	mV Max

DC Electrical Characteristics (Continued)

The following specifications apply for Supply Voltage = $\pm 15\text{V}$, $V_{CM} = 0$, $R_L \geq 100\text{ k}\Omega$ and $R_S = 50\Omega$ unless otherwise noted. **Boldface** limits apply for $T_A = T_J = T_{MIN}$ to T_{MAX} ; all other limits $T_A = T_J = 25^\circ\text{C}$.

Symbol	Parameter	Conditions	Typ	LM6125	LM6225	LM6325	Units
				Limit (Notes 5, 10)	Limit (Note 5)	Limit (Note 5)	
I_{OH}	Flag Pin Output High Current	V_{OH} Flag Pin = 15V (Note 6)	0.01	10 20	10 20	10 20	μA Max
V_{TH}	Shutdown Threshold		1.4				V
V_{IH}	Shutdown Pin Trip Point High			2.0 2.0	2.0 2.0	2.0 2.0	V Min
V_{IL}	Shutdown Pin Trip Point Low			0.8 0.8	0.8 0.8	0.8 0.8	V Max
I_{IL}	Shutdown Pin Input Low Current	$V_{S/D} = 0\text{V}$	-0.07	-10 -20	-10 -20	-10 -20	μA Max
I_{IH}	Shutdown Pin Input High Current	$V_{S/D} = 5\text{V}$	-0.05	-10 -20	-10 -20	-10 -20	μA Max
I_O	Bi-State Output Current	Shutdown Pin = 0V $V_{OUT} = +5\text{V}$ or -5V	1	50 2000	50 100	100 200	μA

AC Electrical Characteristics

The following specifications apply for Supply Voltage = $\pm 15\text{V}$, $V_{CM} = 0$, $R_L \geq 100\text{ k}\Omega$ and $R_S = 50\Omega$ unless otherwise noted. **Boldface** limits apply for $T_A = T_J = T_{MIN}$ to T_{MAX} ; all other limits $T_A = T_J = 25^\circ\text{C}$.

Symbol	Parameter	Conditions	Typ	LM6125	LM6225	LM6325	Units
				Limit (Note 5)	Limit (Note 5)	Limit (Note 5)	
SR_1	Slew Rate 1	$V_{IN} = \pm 11\text{V}$, $R_L = 1\text{ k}\Omega$	1200				$\text{V}/\mu\text{s}$ Min
SR_2	Slew Rate 2	$V_{IN} = \pm 11\text{V}$, $R_L = 50\Omega$ (Note 8)	800	550	550	550	
SR_3	Slew Rate 3	$V_{IN} = 2\text{ V}_{PP}$, $R_L = 50\Omega$ $V_+ = 5\text{V}$ (Note 6)	50				
BW	-3 dB Bandwidth	$V_{IN} = 100\text{ mV}_{PP}$ $R_L = 50\Omega$, $C_L \leq 10\text{ pF}$	50	30	30	30	MHz Min
t_r , t_f	Rise Time Fall Time	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$ $V_O = 100\text{ mV}_{PP}$	8.0				ns
t_{PD}	Propagation Delay Time	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$ $V_O = 100\text{ mV}_{PP}$	4.0				ns
O_S	Overshoot	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$ $V_O = 100\text{ mV}_{PP}$	10				%
V_{FT}	V_{IN} , V_{OUT} Feedthrough in Shutdown	Shutdown Pin = 0V $V_{IN} = 4\text{ V}_{PP}$, 1 MHz $R_L = 50\Omega$	-50				dB
C_{OUT}	Output Capacitance in Shutdown	Shutdown Pin = 0V	30				pF
t_{SD}	Shutdown Response Time		700				ns

Note 2: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications do not apply when operating the device beyond its rated operating conditions.

Note 3: During current limit, thermal limit, or electronic shutdown the input current will increase if the input to output differential voltage exceeds 8V. See Overvoltage Protection in Application Hints.

Note 4: The LM6125 series buffers contain current limit and thermal shutdown to protect against fault conditions.

AC Electrical Characteristics (Continued)

Note 5: For operation at elevated temperature, these devices must be derated based on a thermal resistance of θ_{JA} and T_J max, $T_J = T_A + \theta_{JA} P_D$. θ_{JC} for the LM6125H and LM6225H is 17°C/W. The thermal impedance θ_{JA} of the device in the N package is 40°C/W when soldered directly to a printed circuit board, and the heat-sinking pins (pins 3, 4, 5, 10, 11, and 12) are connected to 2 square inches of 2 oz. copper. When installed in a socket, the thermal impedance θ_{JA} of the N package is 60°C/W.

Note 6: Limits are guaranteed by testing or correlation.

Note 7: The input is biased to +2.5V, and V_{IN} swings V_{PP} about this value. The input swing is 2 V_{PP} at all temperatures except for the A_V3 test at -55°C where it is reduced to 1.5 V_{PP}.

Note 8: The Error Flag is set (low) during current limit or thermal fault detection in addition to being set by the Shutdown pin. It is an open-collector output which requires an external pullup resistor.


Note 9: Slew rate is measured with a $\pm 11V$ input pulse and 50 Ω source impedance at 25°C. Since voltage gain is typically 0.9 driving a 50 Ω load, the output swing will be approximately $\pm 10V$. Slew rate is calculated for transitions between $\pm 5V$ levels on both rising and falling edges. A high speed measurement is done to minimize device heating. For slew rate versus junction temperature see typical performance curves. The input pulse amplitude should be reduced to $\pm 10V$ for measurements at temperature extremes. For accurate measurements, the input slew rate should be at least 1700 V/ μs .

Note 10: The test circuit consists of the human body model of 120 pF in series with 1500 Ω .


Note 11: A military RETS specification is available on request. At the time of printing, the LM6125H/883 RETS spec complied with the Boldface limits in this column. The LM6125H/883 may also be procured as Standard Military Drawing specification #5962-9081501MXX.

Typical Performance Characteristics $T_A = 25^\circ C$, $V_S = \pm 15V$ unless otherwise specified


Frequency Response




Frequency Response




Slew Rate vs Temperature




Overshoot vs Capacitive Load




Large Signal Response
($R_L = 1 k\Omega$)




Large Signal Response
($R_L = 50\Omega$)




Supply Current



-3 dB Bandwidth




Slew Rate




Typical Performance Characteristics $T_A = 25^\circ\text{C}$, $V_S = \pm 15\text{V}$ unless otherwise specified (Continued)


Slew Rate




Power Bandwidth




Input Return Gain (S11)




Forward Transmission Gain (S21)



Current Limit



Typical Connection Diagram



Application Hints

POWER SUPPLY DECOUPLING

The method of supply bypassing is not critical for stability of the LM6125 series buffers. However, their high current output combined with high slew rate can result in significant voltage transients on the power supply lines if much inductance is present. For example, a slew rate of 900 V/ μ s into a 50 Ω load produces a di/dt of 18 A/ μ s. Multiplying this by a wiring inductance of 50 nH results in a 0.9V transient. To minimize this problem use high quality decoupling very close to the device. Suggested values are a 0.1 μ F ceramic in parallel with one or two 2.2 μ F tantalums. A ground plane is recommended.

LOAD IMPEDANCE

The LM6125 is stable into any load when driven by a 50 Ω source. As shown in the *Overshoot vs Capacitive Load* graph, worst case is a purely capacitive load of about 1000 pF. Shunting the load capacitance with a resistor will reduce overshoot.

SOURCE INDUCTANCE

Like any high-frequency buffer, the LM6125 can oscillate at high values of source inductance. The worst case condition occurs at a purely capacitive load of 50 pF where up to 100 nH of source inductance can be tolerated. With a 50 Ω load, this goes up to 200 nH. This sensitivity may be reduced at the expense of a slight reduction in bandwidth by adding a resistor in series with the buffer input. A 100 Ω resistor will ensure stability with source inductances up to 400 nH with any load.

ERROR FLAG LOGIC

The Error Flag pin is an open-collector output which requires an external pull-up resistor. Flag voltage is HIGH during operation, and is LOW during a fault condition. A fault condition occurs if either the internal current limit or the thermal shut-

down is activated, or the shutdown (S/D) pin is driven low by external logic. Flag voltage returns to its HIGH state when normal operation resumes.

If the S/D pin is not to be used, it should be connected to V⁺.

OVERVOLTAGE PROTECTION

The LM6125 may be severely damaged or destroyed if the Absolute Maximum Rating of 7V between input and output pins is exceeded.

If the buffer's input-to-output differential voltage is allowed to exceed 7V, a base-emitter junction will be in reverse-breakdown, and will be in series with a forward-biased base-emitter junction. Referring to the LM6125 simplified schematic, the transistors involved are Q1 and Q3 for positive inputs, and Q2 and Q4 for negative inputs. If any current is allowed to flow through these junctions, localized heating of the reverse-biased junction will occur, potentially causing damage. The effect of the damage is typically increased offset voltage, increased bias current, and/or degraded AC performance. The damage is cumulative, and may eventually result in complete device failure.

The device is best protected by the insertion of the parallel combination of a 100 k Ω resistor (R1) and a small capacitor (C1) in series with the buffer input, and a 100 k Ω resistor (R2) from input to output of the buffer (see *Figure 1*). This network normally has no effect on the buffer output. However, if the buffer's current limit or shutdown is activated, and the output has a ground-referred load of significantly less than 100 k Ω , a large input-to-output voltage may be present. R1 and R2 then form a voltage divider, keeping the input-output differential below the 7V Maximum Rating for input voltages up to 14V. This protection network should be sufficient to protect the LM6125 from the output of nearly any op amp which is operated on supply voltages of \pm 15V or lower.






FIGURE 1. LM6125 with Overvoltage Protection

Physical Dimensions inches (millimeters) unless otherwise noted



Metal Can Package (H)
Order Number LM6125H/883 or LM6125H
NS Package Number H08C



Molded Dual-In-Line Package (N)
Order Number LM6225N or LM6325N
NS Package Number N14A

Notes

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



National Semiconductor Corporation
Americas
Tel: 1-800-272-9959
Fax: 1-800-737-7018
Email: support@nsc.com

www.national.com

National Semiconductor Europe
Fax: +49 (0) 1 80-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 1 80-530 85 85
English Tel: +49 (0) 1 80-532 78 32
Français Tel: +49 (0) 1 80-532 93 58
Italiano Tel: +49 (0) 1 80-534 16 80

National Semiconductor Asia Pacific Customer Response Group
Tel: 65-2544466
Fax: 65-2504466
Email: sea.support@nsc.com

National Semiconductor Japan Ltd.
Tel: 81-3-5639-7560
Fax: 81-3-5639-7507

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Transportation and Automotive	www.ti.com/automotive
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated