


Pentoda

DL 98


Mullard

Wzmacniacz końcowy w.cz.

Heptal



$U_z = 2,5; 1,25 \text{ V}$
 $I_z = 165; 330 \text{ mA}$



Wartości charakterystyczne

Wartości robocze

Wartości graniczne

| | | | |
|-------------|------|------|------------|
| U_a | 90 | 135 | V |
| U_{s2} | 90 | 120 | V |
| I_a | 15 | 30 | mA |
| I_{s2} | 1,0 | 1,8 | mA |
| S_a | 1,7 | 2,15 | mA/V |
| Q_a | 22 | 22 | k Ω |
| $K_{s2/s1}$ | 3,2 | 3,45 | V/V |
| U_{s1} | -9,9 | -10 | V |

Wzm. kl. A lub oscylator

| | | | |
|-----------|------|------|---------|
| f | 100 | 100 | MHz |
| U_a | 90 | 150 | V |
| U_{s2} | 90 | 135 | V |
| U_{s1} | -18 | -39 | V |
| I_a | 15 | 25 | mA |
| I_{s2} | 4,8 | 6,2 | mA |
| I_{s1} | 400 | 550 | μ A |
| P_{wej} | 30 | 70 | mW |
| P_a | 0,45 | 1,25 | W |

| | | |
|---------------|-----|------------|
| U_{amax} | 150 | V |
| P_{amax} | 3,0 | W |
| U_{s2max} | 135 | V |
| P_{s2max} | 1,1 | W |
| $-U_{s1max}$ | 75 | V |
| I_{amax} | 25 | mA |
| I_{s1max} | 1,5 | mA |
| $R_{s1/kmax}$ | 100 | k Ω |
| I_{kmax} | 32 | mA |

Pojemności

| | | |
|------------|------|-----|
| $C_{a/s1}$ | <160 | mpF |
| C_{wej} | 4,6 | pF |
| C_{wyj} | 7,6 | pF |

TYPY PODOBNE

3 B 4; CV 2240

