

T.	Image	Image	$U_f$	$I_f$	$U_{tr}$	$U_p$	$I_o$	$I_p$	$R_1$	$R_2$	$U_{f/k}$	$C_f$	Fig.
			V	A	V	V	mA	mA	$\Omega$	$\Omega$	V	$\mu F$	
35 W 4	int	1	35	0,15	110	700	100	600	15		350	40	1
					220								
35 X 4	int	2	35	0,15	110	700	90	600	15		350	40	1
					110								
35 Y 4	amer	3	35	0,15	110		80		15	150		40	2
35 Z 3	int	4	35	0,15	110		90		15	100		40	2
35 Z 4	int	5	35	0,15	220		60		100			40	2
35 Z 5-G	int	6	35	0,15	220		70		100	300		40	2
					220		80		100	150		40	2
					220		90		100	100		40	2

### Equivalents

HY 90	eur	=	35W 4
35 Y 5	amer	=	35 Y 4
35 Z 3-LT	Syl	=	35 Z 3
35 Z 5-GT	int	=	35 Z 5

