TOSHIBA CMOS DIGITAL INTEGRATED CIRCUIT SILICON MONOLITHIC

TC74HC279AP, TC74HC279AF

QUAD S-R LATCH

The TC74HC279A is a high speed CMOS QUAD S-R LATCH fabricated with silicon gate C²MOS technology.

It achieves the high speed operation similar to equivalent LSTTL while maintaining the CMOS low power dissipation. Each latch has an independent Q output and Set and Reset


inputs. \overline{S} and \overline{R} are active low. When \overline{S} input is low, the Q output goes high and when \overline{R} input is low, the Q output goes low. When both \overline{S} and \overline{R} are low, \overline{S} takes precedence resulting Q=low. When both of \overline{S} and \overline{R} are held high, Q output doesn't change.

All inputs are equipped with protection circuits against static discharge or transient excess voltage.


FEATURES:

TRUTH TABLE

- High Speed······ t_{pd} = 12ns(typ.) at V_{CC} = 5V
- Low Power Dissipation ··········· $I_{CC} = 2\mu A(Max.)$ at Ta = 25°C
- High Noise Immunity $V_{NIH} = V_{NIL} = 28\% V_{CC}$ (Min.)
- Symmetrical Output Impedance... $| I_{OH} | = I_{OL} = 4mA(Min.)$
- Balanced Propagation Delays $\cdots t_{pLH} \approx t_{pHL}$
- Wide Operating Voltage Range ···· V_{CC} (opr.) = 2V~6V
- Pin and Function Compatible with 74LS279



PIN ASSIGNMENT



IEC LOGIC SYMBOL


INP	OUTPUTS			
S #	R	Q		
Н	Н	Qn		
L	Н	Н		
Н	L	L		
L	L	Н		

NOTE:

-- The level of Q before the indicated input

condition were established.

-- For latches with doubles \overline{S} input. $H = Both \ \overline{S}$ input high $L = One \ of \ both \ inputs \ low$



ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	VALUE	UNIT
Supply Voltage Range	V_{CC}	− 0.5~7	٧
DC Input Voltage	VIN	$-0.5 \sim V_{CC} + 0.5$	٧
DC Output Voltage	V _{OUT}	$-0.5 \sim V_{CC} + 0.5$	٧
Input Diode Current	I _{IK}	± 20	mA
Output Diode Current	I _{OK}	± 20	mA
DC Output Current	I _{OUT}	± 25	mA
DC V _{CC} / Ground Current	I _{cc}	± 50	mA
Power Dissipation	P _D	500 (DIP)* / 180 (SOP)	mW
Storage Temperature	T _{stg}	−65~150	°C

*500mW in the range of Ta= $-40^{\circ}\text{C}\sim65^{\circ}\text{C}$. From Ta= 65°C to 85 °C a derating factor of $-10\text{mW}/^{\circ}\text{C}$ shall be applied until 300mW.

RECOMMENDED OPERATING CONDITIONS

PARAMETER	SYMBOL	VALUE	UNIT
Supply Voltage	V _{cc}	2~6	V
Input Voltage	V _{IN}	0~V _{cc}	٧
Output Voltage	V _{OUT}	0~V _{CC}	V
Operating Temperature	T _{opr}	−40~85	°C
Input Rise and Fall Time	t _r , t _f	$0 \sim 1000 (V_{CC} = 2.0V)$ $0 \sim 500 (V_{CC} = 4.5V)$ $0 \sim 400 (V_{CC} = 6.0V)$	ns

DC ELECTRICAL CHARACTERISTICS

PARAMETER	CVAADOL	TEST CONDITION		V _{cc}	Ta = 25°C			Ta = −40~85°C		UNIT
PARAIVIETER	SYMBOL	1531 CC	MUITION	(v)	MIN.	TYP.	MAX.	MIN.	MAX.	OINII
High - Level Input Voltage	VIH				1.50 3.15 4.20	_ _ _	_ _ _	1.50 3.15 4.20		v
Low - Level Input Voltage	VIL			2.0 4.5 6.0			0.50 1.35 1.80	_ _ _	0.50 1.35 1.80	v
High - Level Output Voltage	V _{OH}	V _{IN} = V _{IH} or V _{IL}	$I_{OH} = -20\mu A$	2.0 4.5 6.0	1.9 4.4 5.9	2.0 4.5 6.0	_ _ _	1.9 4.4 5.9		V
			$I_{OH} = -4 \text{ mA}$ $I_{OH} = -5.2 \text{ mA}$	4.5 6.0	4.18 5.68	4.31 5.80	_	4.13 5.63	_	
Low - Level Output Voltage	V _{I N} =	$I_{OL} = 20 \mu A$	2.0 4.5 6.0		0.0 0.0 0.0	0.1 0.1 0.1	_ _ _	0.1 0.1 0.1	v	
	V _{IH} or V _{IL}	$I_{OL} = 4 mA$ $I_{OL} = 5.2 mA$	4.5 6.0	1 1	0.17 0.18	0.26 0.26	_ _	0.33 0.33		
Input Leakage Current	I _{IN}	$V_{IN} = V_{CC}$ or GND		6.0	1	ı	± 0.1	_	± 1.0	
Quiescent Supply Current	I _{CC}	$V_{IN} = V_{CC}$ or GND		6.0	_	_	2.0	_	20.0	μΑ

AC ELECTRICAL CHARACTERISTICS ($C_L = 15pF$, $V_{CC} = 5V$, $Ta = 25^{\circ}C$, Input $t_r = t_f = 6ns$)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Transition Time	t _{TLH} t _{THL}		_	4	8	
Propagation Delay Time $(\overline{S}1, \overline{S}2-Q)$	t _{pLH} t _{pHL}		_	12	22	ns
Propagation Delay Time $(\overline{S} - Q)$	t _{pLH} t _{pHL}		_	9	17	113
Propagation Delay Time $(\overline{R}-Q)$	t _{pLH} t _{pHL}		_	11	20	

AC ELECTRICAL CHARACTERISTICS ($C_L = 50pF$, Input $t_r = t_f = 6ns$)


PARAMETER	SYMBOL	TEST CONDITION		Ta = 25°C		Ta = −40~85°C		UNIT	
			$V_{CC}(V)$	MIN.	TYP.	MAX.	MIN.	MAX.	UNIT
	t _{TLH}		2.0	_	30	75	_	95	
Output Transition Time			4.5	_	8	15	_	19	
	t _{THL}		6.0	_	7	13	_	16	
Propagation Delay Time	+		2.0	_	45	130	_	165	
	t _{pLH}		4.5	_	15	26	_	33	
$(\overline{S}1, \overline{S}2-Q)$	t _{pHL}		6.0	_	13	22	_	28	
Propagation Delay Time	+		2.0	_	38	100	_	125	ns
	t _{pLH}		4.5	_	12	20	_	25	
	t _{pHL}		6.0	_	10	17	_	21	
Propagation Delay Time $(\overline{R} - Q)$	+		2.0	_	42	120	_	150	
	t _{pLH}		4.5	_	14	24	_	30	
	τ_{pHL}		6.0	_	12	20	_	26	
Input Capacitance	C _{IN}			_	5	10	_	10	nE
Power Dissipation Capacitance	C _{PD} (1)			-	18	_	_	_	pF

Note (1) C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.

Average operating current can be obtained by the equation:


 I_{CC} (opr) = $C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC} / 4$ (per circuit)

SYSTEM DIAGRAM




DIP 16PIN PACKAGE DIMENSIONS (DIP16-P-300-2.54A)

Unit in mm



SOP 16PIN (200mil BODY) PACKAGE DIMENSIONS (SOP16-P-300-1.27)

Unit in mm



RESTRICTIONS ON PRODUCT USE

000707EBA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The products described in this document are subject to the foreign exchange and foreign trade laws.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.