

Pentoda strumieniowa

1Q5-GT


Wzmacniacz mocy kl. A

Oktal

1Q5-GT

$$U_z = 1,4 \text{ V}$$

$$I_z = 0,1 \text{ A}$$



Wartości robocze

U_a	85	90	V
U_{s2}	85	90	V
U_{s1}	-5	-4,5	V
$U_{s1} \sim \text{szcz}$	5	4,5	V
I_{a0}	7,0	9,5	mA
I_{s20}	0,8	1,3	mA
S_a	1,95	2,20	mA/V
g_a	70	75	k Ω
R_a	9	8	k Ω
$P_{a\sim}$	250	270	mW
h	5,5	6,0	%

Wartości maksymalne

U_{amax}	110	V
U_{s2max}	110	V
I_{k0max}	12	mA

TYPY PODOBNE

1Q5-G, DL 11, DL 36

