


Podwójna dioda


6CA4

Przestownik pełnokresowy

Nowal



$U_z = 6,3V$
 $I_z = 600 mA$



Wartości maksymalne

U_{tr}	2×200	2×250	2×350	V
I_{Σ}	90	90	90	mA
U_{Σ}	230	265	360	V
R	2×75	2×125	2×300	Ω
C_L	50	50	50	μF
		$U_{wlkszcz}$	500	V

TYPY PODOBNE

EZ 81